

PCT

WORLD INTELLECTUAL PROPERTY ORGANIZATION  
International Bureau



INTERNATIONAL APPLICATION PUBLISHED UNDER THE PATENT COOPERATION TREATY (PCT)

(51) International Patent Classification 6 :

G01K 15/00

A1

(11) International Publication Number:

WO 98/13677

(43) International Publication Date:

2 April 1998 (02.04.98)

(21) International Application Number: PCT/US97/17068

(22) International Filing Date: 24 September 1997 (24.09.97)

(30) Priority Data:  
08/718,921 25 September 1996 (25.09.96) US

(71) Applicant: CLAUD S. GORDON COMPANY [US/US]: 5710  
Kenosha Street, Richmond, IL 60071 (US).

(72) Inventor: SCHUH, William, C.; 218 Matthew Street, Delavan,  
WI 53115 (US).


(74) Agent: ESCHWEILER, Thomas, G.; Reiner, Otto, Boisselle  
& Sklar, P.L.L., 19th floor, 1521 Euclid Avenue, Cleveland,  
OH 44115 (US).

(81) Designated States: AL, AM, AT, AU, AZ, BA, BB, BG, BR,  
BY, CA, CH, CN, CU, CZ, DE, DK, EE, ES, FI, GB, GE,  
GH, HU, IL, IS, JP, KE, KG, KP, KR, KZ, LC, LK, LR,  
LS, LT, LU, LV, MD, MG, MK, MN, MW, MX, NO, NZ,  
PL, PT, RO, RU, SD, SE, SG, SI, SK, SL, TJ, TM, TR,  
TT, UA, UG, UZ, VN, YU, ZW, ARIPO patent (GH, KE,  
LS, MW, SD, SZ, UG, ZW), Eurasian patent (AM, AZ, BY,  
KG, KZ, MD, RU, TJ, TM), European patent (AT, BE, CH,  
DE, DK, ES, FI, FR, GB, GR, IE, IT, LU, MC, NL, PT,  
SE), OAPI patent (BF, BJ, CF, CG, CI, CM, GA, GN, ML,  
MR, NE, SN, TD, TG).

Published

With international search report.  
Before the expiration of the time limit for amending the  
claims and to be republished in the event of the receipt of  
amendments.

(54) Title: SMART TEMPERATURE SENSING DEVICE



(57) Abstract

A smart temperature sensing device (10) includes a sensor (16) and a memory (25) on a sensor unit (14). The memory contains a plurality of custom nonlinear calibration coefficients which uniquely characterize the sensor (16). A temperature system includes the smart temperature sensing device (10) and a FSAU (12) having a processor (28) which downloads the calibration coefficients and utilizes them in converting electrical signals from the sensor (16) into temperature values that represent the temperature at the sensor (16). A method of calibrating a sensor (16) includes measuring an output signal of the sensor (16) over a temperature range, thereby obtaining a plurality of paired data points. The paired data points are used in a curve-fitting algorithm to obtain coefficients to a polynomial that characterizes the nonlinear temperature-voltage relationship of the sensor (16). The coefficients are stored within the memory (25) until downloaded by the processor (28) for use in signal conversion.

BEST AVAILABLE COPY

*FOR THE PURPOSES OF INFORMATION ONLY*

Codes used to identify States party to the PCT on the front pages of pamphlets publishing international applications under the PCT.

AL	Albania	ES	Spain	LS	Lesotho	SI	Slovenia
AM	Armenia	FI	Finland	LT	Lithuania	SK	Slovakia
AT	Austria	FR	France	LU	Luxembourg	SN	Senegal
AU	Australia	GA	Gabon	LV	Latvia	SZ	Swaziland
AZ	Azerbaijan	GB	United Kingdom	MC	Monaco	TD	Chad
BA	Bosnia and Herzegovina	GE	Georgia	MD	Republic of Moldova	TG	Togo
BB	Barbados	GH	Ghana	MG	Madagascar	TJ	Tajikistan
BE	Belgium	GN	Guinea	MK	The former Yugoslav Republic of Macedonia	TM	Turkmenistan
BF	Burkina Faso	GR	Greece			TR	Turkey
BG	Bulgaria	HU	Hungary	ML	Mali	TT	Trinidad and Tobago
BJ	Benin	IE	Ireland	MN	Mongolia	UA	Ukraine
BR	Brazil	IL	Israel	MR	Mauritania	UG	Uganda
BY	Belarus	IS	Iceland	MW	Malawi	US	United States of America
CA	Canada	IT	Italy	MX	Mexico	UZ	Uzbekistan
CF	Central African Republic	JP	Japan	NE	Niger	VN	Viet Nam
CG	Congo	KE	Kenya	NL	Netherlands	YU	Yugoslavia
CH	Switzerland	KG	Kyrgyzstan	NO	Norway	ZW	Zimbabwe
CI	Côte d'Ivoire	KP	Democratic People's Republic of Korea	NZ	New Zealand		
CM	Cameroon			PL	Poland		
CN	China	KR	Republic of Korea	PT	Portugal		
CU	Cuba	KZ	Kazakstan	RO	Romania		
CZ	Czech Republic	LC	Saint Lucia	RU	Russian Federation		
DE	Germany	LI	Liechtenstein	SD	Sudan		
DK	Denmark	LK	Sri Lanka	SE	Sweden		
EE	Estonia	LR	Liberia	SG	Singapore		

**Title: SMART TEMPERATURE SENSING DEVICE**

**FIELD OF THE INVENTION**

5 This invention generally relates to a temperature sensing device. More particularly, the invention relates to a pre-programmed smart temperature sensor having custom calibration coefficients uniquely characterizing the sensor stored in a memory local to the sensor.

**BACKGROUND OF THE INVENTION**

10 Many applications require sensing of a temperature to effectuate a task. One typical way of sensing a temperature is to place a temperature sensor within the environment to be sensed. The temperature sensor conveys an electrical signal, which is indicative of the temperature of the environment, to electrical conversion circuitry which converts the electrical signal into a temperature and subsequently displays it to a user. A  
15 problem often arises, however, in that many conventional prior art temperature sensing solutions do not provide for highly accurate temperature readings because the sensors are not adequately calibrated for use with the electrical conversion circuitry.

One prior art solution to this problem was to calibrate a given sensor over a temperature range by placing general calibration information into a memory associated  
20 with the conversion circuitry. This general calibration information suffered from the drawback that each sensor in use is not identical, but rather has its own internal variations. Therefore, the general calibration data used within the electrical conversion circuitry did not provide for an accurate temperature reading for any one particular sensor.

Another solution involved calibrating a given sensor over a number of different  
25 temperatures and storing calibration information within a memory associated with the electrical conversion circuitry. In this manner, the sensor was calibrated and had unique calibration information associated with it in the electrical conversion circuitry. This solution, however, suffered from the drawback that the useful life of a sensor is often substantially shorter than the useful life of the conversion circuitry. Therefore, when a  
30 sensor needed to be replaced, the unique calibration information within the electrical conversion circuitry was no longer applicable to a replacement sensor. Whenever a sensor needed to be replaced (which was frequent), a user needed to replace both the

5 sensor and the substantially more expensive electrical conversion circuitry. This resulted in high cost and expense to the user.

In addition to the above prior art limitations, prior art methods of calibrating a sensor consisted of using linear approximations to characterize a sensor over a temperature range. In this manner, typical linear conversion methodologies such as look-up tables were utilized, but the linear approximations provided poor accuracy since  
10 temperature sensors do not behave linearly over a broad range of temperatures. Therefore, even when a sensor was calibrated, its calibration consisted of inaccurate linear approximations.

### SUMMARY OF THE INVENTION

15 In one aspect of the invention, a temperature sensing device includes a sensor and a memory coupled together on a holder, wherein the memory contains a plurality of custom calibration coefficients which uniquely characterize the sensor. The smart sensing device may also have a remote processor coupled to the sensor. The remote processor is operable to access the plurality of calibration coefficients from the memory and an  
20 electrical signal from the sensor. The remote processor calculates the temperature value at the sensor by utilizing the calibration coefficients in conjunction with the electrical signal. The sensor and the memory are resident together on the holder used in taking the thermal measurement; therefore the sensor and memory are local to the sensed environment while the processor is remote from the holder, yet remains in electrical  
25 communication with the sensor and the memory. The memory may also contain other pieces of custom data which is uniquely associated with the sensor such as time constant data, maintenance data, intended use data, regulatory data or cold junction compensation coefficients to further aid in accurately determining the temperature at the sensor and improve sensor reliability.

30 In another aspect of the invention, a method of calibrating a thermal sensor includes measuring an output signal of the sensor over a temperature range, thereby obtaining a plurality of paired data points. The method also includes the step of utilizing the paired data points in a mathematical curve fitting algorithm to obtain coefficients to a polynomial that characterizes the performance of the sensor over the temperature range.

5 The calibration coefficients are then stored within a memory which is associated with the sensor.

10 In yet another aspect of the invention, a method of making thermal measurements includes a step of sending calibration data from a sensor to a processor, wherein the calibration data represents calibration information which uniquely characterizes the sensor. The method also includes the steps of measuring a temperature at the sensor, communicating an electrical signal from the sensor to the processor, and converting the electrical signal into a temperature reading via the processor by utilizing the calibration data in a conversion algorithm.

15 In a further aspect of the invention, a method of providing custom calibration sensors for measuring temperature includes the step of measuring a voltage or resistance value of a thermal sensor over a range of temperatures, and calculating a plurality of custom calibration coefficients which uniquely characterize the sensor using the calibration coefficients. The method also includes the step of storing the custom calibration coefficients in the memory associated with the sensor.

## 20 BRIEF DESCRIPTION OF THE DRAWINGS

In the annexed drawings:

Figure 1 is a block diagram illustrating a smart temperature sensing device coupled to a field signal acquisition unit in accordance with the present invention;

25 Figure 2 is a schematic diagram illustrating the smart temperature sensing device coupled to the field signal acquisition unit;

Figure 3 is a detailed block diagram of the smart temperature sensing device and the field signal acquisition unit;

Figure 4 is a schematic diagram illustrating the smart temperature sensing device coupled to a computer;

30 Figure 5 is a table illustrating a plurality of paired temperature data points and calibration coefficients;

Figure 6 is a schematic diagram illustrating the computer coupled to the memory of the smart temperature sensing device;

35 Figure 7 is a graph exemplifying the error associated with linear approximations of the voltage-temperature relationship of sensors;

5 Figure 8 is a schematic diagram illustrating in greater detail the smart temperature sensing device, illustrating the memory and an RTD-type temperature sensor; and

Figure 9 is a schematic diagram illustrating in greater detail a smart temperature sensing device according to another embodiment including a thermocouple-type temperature sensor and the memory.

### 10 DETAILED DESCRIPTION OF THE INVENTION

The invention relates to a calibrated smart temperature sensing device having nonlinear calibration data which reflects a historical nonlinear behavior of a class of sensors over a temperature range. The nonlinear calibration data (or coefficients) are stored in a memory within a sensor unit which includes a sensor. When in use, the smart temperature sensing device is in electrical communication with a field signal acquisition unit (or conversion circuitry) which downloads the calibration coefficients from the memory of the smart temperature sensing device. The smart temperature sensing device transfers a signal to the field signal acquisition unit which is indicative of the temperature at the sensor which converts the signal into a temperature using the nonlinear calibration coefficients of the smart temperature sensing device.

15 The smart temperature sensing device may alternatively contain custom calibration data which uniquely characterizes the sensor. Prior to use, the smart temperature sensing device is calibrated over a range of temperatures by measuring its output signal over a temperature range and calculating custom nonlinear calibration coefficients. The calculation of the custom nonlinear calibration coefficients may be accomplished using a least squares fitting algorithm. The calibration coefficients uniquely characterize the sensor and are stored in the memory within the sensor unit. The smart temperature sensing device provides high accuracy by using the custom calibration coefficients that uniquely characterize each sensor. Further, the custom calibration coefficients provide high accuracy because they are nonlinear coefficients that satisfy a polynomial which accurately characterizes the nonlinear behavior of the sensor over the temperature range.

25 The smart temperature sensing device may also provide additional information to the field signal acquisition unit; such additional information includes:

30

5 a time constant for sensor speed of response, maintenance data based on the sensor type, intended use environment data for sensor drift, regulatory information that may be specific to a particular customer, and cold junction compensation coefficients for thermocouple-type sensor.

10 Figure 1 is a block diagram illustrating a smart temperature sensing device 10 coupled to a field signal acquisition unit (FSAU) 12. The smart temperature sensing device 10 senses a temperature of its environment and sends an analog electronic signal to the FSAU 12. The FSAU 12, in turn, converts the electrical signal from the smart sensing device 10 into a value indicative of the temperature of the environment.

15 Figure 2 is a schematic diagram illustrating in greater detail the smart temperature sensing device 10 coupled to the FSAU 12. The smart temperature sensing device 10, in one embodiment, comprises a sensor unit 14 including a handle portion 15 and a temperature sensor 16 coupled together via a spacer portion 18. The spacer portion 18 serves to provide a suitable distance between the handle portion 15 and the temperature sensor 16 under circumstances in which the thermal environment at the temperature sensor portion 16 is substantially hot or cold to protect any plastic materials, electronics, or potting compounds associated with the sensor unit 14 from thermal damage and protect a user's hand on the handle portion 15 from suffering any discomfort. Alternatively, the smart temperature sensing device 10 could operate without the spacer portion 18 and thereby incorporate the handle portion 15 and the temperature sensor 16 together on or within the same sensor unit 14. In an alternative embodiment, the smart temperature sensing device 10 may further isolate the sensor unit 14 from the temperature sensor 16 by incorporating each into separate housings or subunits, wherein both remain separate from the FSAU 12.

20 The smart temperature sensing device 10 is coupled to the FSAU 12 through a wire connector 20. The FSAU 12 includes a display 22, control knobs 24, and conversion circuitry (not shown) which is internal to the FSAU 12 and converts the analog electrical signal from the smart temperature sensing device 10 into a value representative of the temperature at the temperature sensor 16. The FSAU 12 displays the temperature on the display 22 and the control knobs 24 (which are optional) are used to alter the contrast of the display 22, convert the temperature display from degrees Fahrenheit to degrees  
25  
30  
35

5 Celsius or alternatively to degrees Kelvin, or provide other control functions. Alternatively, the FSAU 12 may include additional buttons or other control indicia to effectuate conversion functions.

10 Figure 3 is a block diagram illustrating the internal circuitry of both the smart temperature sensing device 10 and the FSAU 12. The smart temperature sensing device 10 has a memory 25 and the temperature sensor 16 coupled to a noise suppression circuit 26. The memory 25 and the noise suppression circuit 26 are connected to the FSAU 12 through a P2 connector 27, which is a common parallel-type connector, which couples the smart temperature sensing device 10 and the FSAU 12 together. Alternatively, a different type of connector may also be utilized such as a bundled wire harness. The FSAU 12 includes a processor 28 connected to a memory 30, an analog-to-digital converter 32, and the display 22. The memory 25 of the smart temperature sensing device 10 is coupled to the processor 28 via the P2 connector 27, and the noise suppression circuit 26 is coupled to the analog-to-digital converter 32 as well. Alternatively, the memory 25 may be located in either the handle portion 15, the spacer portion 18 or the connector 27 where, in each case, the memory 26 is separate from the FSAU 12.

20 The smart temperature sensing device 10 works in conjunction with the FSAU 12 in the following manner. The memory 25 of the smart temperature sensing device 10 contains, in one embodiment, historical calibration data that characterizes the nonlinear behavior of a class of sensors over temperature. For example, if the temperature sensor 25 16 is a thermocouple-type sensor, the nonlinear historical calibration data represents the average nonlinear behavior of many thermocouple-type sensors that have been calibrated in the past. In this manner, the historical calibration data represents the average nonlinear behavior for thermocouple-type sensors. Similarly, different nonlinear historical calibration data will be used for other type temperature sensors 16 such as an RTD-type temperature sensor. In another embodiment, the memory 25 of the smart temperature 30 sensing device 10 contains custom calibration data which uniquely characterizes the nonlinear behavior of the temperature sensor 16. Calibration coefficients are determined and loaded into the memory 25; how this is accomplished will be discussed infra. Upon initially coupling the smart temperature sensing device 10 to the FSAU 12 (via the P2 35 connector 27) the processor 28 immediately accesses the memory 25 to download the



5 custom calibration coefficients resident within the memory 25 into the memory 30 of the  
FSAU 12. The temperature sensor 16, upon being placed in its respective temperature  
environment, senses the temperature and outputs an analog electrical signal indicative of  
the temperature. The analog electrical signal, in a preferred embodiment, passes through  
10 the noise suppression circuit 26, which effectively filters the analog electrical signal,  
preferably through a band-pass filter arrangement, and eliminates noise associated with  
the signal. The noise suppression circuit 26 then passes the filtered electrical signal to the  
analog-to-digital converter 32 via the P2 connector 27. The analog-to-digital converter  
32 converts the analog filtered electrical signal into a digital signal (or binary word) for  
15 the processor 28 which converts, using the custom calibration coefficients now resident  
within the memory 30, the digital signal into a temperature value which accurately  
represents the temperature of the environment at the temperature sensor 16. The  
processor 28 converts the electrical signal, which is a voltage (EMF) or resistance value,  
into a temperature through the following algorithm:

20 
$$\text{Temperature} = CO + C1 \cdot \text{EMF} + C2 \cdot \text{EMF}^2 + C3 \cdot \text{EMF}^3 + \dots + C8 \cdot \text{EMF}^8$$
, wherein CO,  
C1...C8 represents the custom calibration coefficients and EMF represents the voltage  
value (typically in millivolts) or resistance value (in ohms). The processor 28 then  
displays that temperature value via the display 22.

The memory 25 within the smart temperature sensing device 10 may also contain  
25 additional data to provide improved conversion accuracy and system reliability. For  
example, the memory 25 may store a time constant associated with the particular  
temperature sensor 16. The time constant represents the time it takes for the temperature  
sensor 16 to respond to a change in temperature. The processor 28 may use the time  
constant data in at least two ways: first, if the temperature sensor 16 is sensing the  
30 temperature at a number of different temperature interactions, the processor 28 knows  
how long to wait to convert the signal from the temperature sensor 16 to ensure that the  
measurement is accurate. Second, if the processor 28 is also controlling the heating or  
cooling of an oven apparatus, it may use the time constant data in a temperature control  
algorithm to more precisely control the temperature.

35 Additional data within the memory 25 may consist of maintenance data regarding  
maintenance scheduling for the temperature sensor 16. For example, if the temperature

5 sensor 16 should be tested or checked every "X" days, the memory 25 may download "X" to the processor 28 which will begin incrementing a clock. When the clock reaches "X", the processor 28 will communicate to the user via the display 22 that the temperature sensor 28 requires maintenance. The data within the memory 25 may include data for temperature sensor type ("X" days for RTDs, "Y" days for thermocouples, etc.) or sensor  
10 use (replace or repair every "Z" measurement).

In addition to the above options, the memory 25 may also contain intended use environment data. For example, temperature sensors 16 experience a known drift when measuring temperatures in a particular environment over time. The processor 28 may use this intended use environment data to approximately offset measured temperatures in that  
15 particular environment over time, thereby accurately taking into account drift within the particular temperature sensor 16. Because drift is a function of the particular environment, the temperature sensor 16 may be uniquely customized for a particular intended use environment.

Regulatory data specific to a particular customer may also be stored within the  
20 memory 25. For example, ISO-9000 specification requirements, internal quality control standards, or UL mandates may require that particular actions be taken at various times to monitor, replace or repair the temperature sensor 16. In a manner similar to the maintenance data, the processor 28 downloads this data and provides prompts to the user via the display 22 to ensure that the regulatory requirements are addressed. Such  
25 regulatory data may also include data on the date of the sensor's manufacture, its material lot, when and where it was tested, a serial number of other traceability information.

Cold junction compensation coefficients for thermocouples may also be downloaded into the memory 25. As is well known for a thermocouple-type sensor, a separate sensor is placed at the cold end of the thermocouple junction and the sensor must  
30 convert its output into an equivalent thermocouple signal in millivolts to subsequently calculate the temperature at its "hot" end. Since each style thermocouple (type K, C, J or T, for example) has its own unique conversion parameters, a universal conversion algorithm results in inaccuracies. Since each temperature sensor 16 (when using a thermocouple-type sensor) will know the style thermocouple being used, the unique compensation  
35 coefficient may be placed within the memory 25 for subsequent use by the processor 28.

5 Therefore, a plethora of data may be placed within the memory 25 which is unique to each temperature sensor 16, thereby providing improved conversion accuracy and sensor reliability.

10 Figure 4 illustrates a calibration system 34 having the smart temperature sensing device 10 coupled to a computer 36. The calibration system 34 is preferably utilized prior to sale of the smart temperature sensing device 10 such that purchase of the smart temperature sensing device 10 will include the custom calibration data already resident with the memory 25. The calibration system operates by placing the sensor unit 14 in a thermal environment having a known temperature. The sensor unit 14 outputs an analog signal to the computer 36 simultaneously with a recording of the known temperature by the computer 36. The thermal environment temperature is known to the computer 36 via a signal from a standard sensing device with verified calibration provided from a reference lab such as NIST. The calibration system 34 then increments the temperature of the thermal environment to a second known temperature and repeats the thermal measurement with the smart temperature sensing device 10. The calibration system 34 repeats the steps until a sufficient number of data points have been collected, whereby the computer 36 then has a number of signal values associated with a number of known temperatures (paired data points). The computer 36 uses an algorithm to calculate a plurality of calibration coefficients for a polynomial which represents a curve which matches the paired data points.

25 Figure 5 is a table which represents the paired data points gathered from the calibration system 34 of Figure 4. Figure 5 has a calibration temperature column 38 which lists a plurality of calibration temperatures; when the calibration system 34 varies the temperature of the environment, that temperature is recorded in the calibration temperature column 38. A sensor output column 40 lists all the analog voltage signal values or resistance from the smart temperature sensing device 10 gathered during the recordation of the calibration system 34. In this manner, the table has a plurality of paired data points, namely the calibration temperature column 38 and the sensor output column 40, wherein an output voltage signal or resistance value is coupled or paired to each respective calibration temperature. The last column in Figure 5 is a calibration coefficient column 42; the computer 36 of the calibration system 34 takes the values for the paired

30

35

5 data points of calibration temperature column 38 and the sensor output column 40 and uses these paired data points to calculate the calibration coefficients. The computer 36 utilizes the plurality of paired data points, in a preferred embodiment, in a least squares fitting algorithm to find a polynomial of minimal degree of the form:

$$\text{Temperature} = CO + C1 * EMF + C2 * EMF^2 + C3 * EMF^3 + \dots + C8 * EMF^8,$$

10 wherein CO, C1, etc. are the calibration coefficients. The least squares fitting may also be artificially weighted so that the temperature at EMF = OV is about 0°C for thermocouple-type sensors. When higher order coefficients are equal to zero, it indicates that an acceptable curve fit was obtained with a polynomial of an order less than eight. The computer 36 downloads the calculated custom calibration coefficients into the memory 25  
15 of the smart temperature sensing device 10 which is illustrated in conjunction with Figure 6.

Figure 6 is a block diagram illustrating the computer 36 connected to the memory 25 of the smart temperature sensing device 10. A memory address portion 43 is located within the memory 25 and represents predetermined, fixed addresses (A0-A8) at which  
20 the custom calibration coefficients reside within the memory 25. The processor 28 of the FSAU 12, when desiring to access the custom calibration coefficients of the memory 25, therefore knows where to look to find the custom calibration coefficients and other information unique to the particular temperature sensor 16.

The use of custom, nonlinear calibration coefficients substantially improves the  
25 conversion accuracy over prior art linear methodologies. The improvement in conversion accuracy is illustrated in Figure 7, which is a graph illustrating a thermocouple-type sensor as an example, having temperature (T) on the X-axis and the signal voltage (V) on the Y-axis. On the graph is a plurality of paired data points 44 ( $t_1, v_1$ ), ( $t_2, v_2$ ), etc. collected in the manner described above in conjunction with Figures 4 and 5. In prior art linear  
30 approximations, a straight line approximation 45 is made using the paired data points. Then, when a voltage signal is received ( $V_0$ ) the corresponding temperature ( $T_1$ ) on the straight line 45 is determined. As can be seen by the plurality of data points on this graph, however, the temperature sensor 16 does not behave in a perfectly linear manner over its temperature range, but rather behaves nonlinearly. In this particular example utilizing the  
35 nonlinear coefficients, the voltage signal ( $V_0$ ) corresponds to a temperature  $T_0$  which is

5 lower than  $T_L$ . The nonlinear coefficients for the polynomial that characterize the nonlinear voltage-temperature relationship 46 eliminate the error ( $\Delta T$ ) associated with prior art linear approximations.

10 Figure 8 is a schematic diagram showing in detail the smart temperature sensing device 10 of Figure 3, namely a resistance temperature device (RTD) 47 coupled to an EEPROM 48. The RTD 47 and the EEPROM 48 represent a detailed representation of the temperature sensor 16 coupled to the memory 25 within the handle portion 14 (or alternatively a separate subunit) of the smart temperature sensing device 10 of Figures 2 and 3. The EEPROM 48 operates in conjunction with the RTD 47 in the following manner. After the computer 36 has gathered the paired data points and calculated the calibration coefficients associated with the particular probe, which in this case is the RTD 15 47, and the user wishes to enable the calibration, the user places a jumper between the part enable pin and the power supply which is coupled to the voltage supply pin of the EEPROM 48. The chip select pin is driven high (by the computer 36) and the calibration coefficient data is incrementally read in (or clocked) through the D0 and D1 pins. When 20 all the calibration coefficient data has been read into the EEPROM 48, the user disconnects the jumper between the part enable pin up and the power supply and subsequently places the jumper between the part enable pin and the ground pin which disables the downloading of calibration coefficients into the memory 25.

25 Upon power-up, the processor 28 reads and downloads the calibration coefficients resident within the EEPROM 48 into the memory 30 associated with the FSAU 12. The processor 28 pulls the chip select pin low which enables data to be read from the memory 25. The calibration coefficient data is clocked out of the D0 and D1 pins and stored in the memory 30 for use by the processor 28. In this manner, the EEPROM 48 communicates the custom calibration coefficients to the processor 28 for use in converting analog signals 30 received from the temperature sensor 16. The RTD 47, in this particular embodiment, senses the temperature by generating the analog signal and communicates that either directly to the analog-to-digital converter 32 or alternatively may send that to the analog-to-digital converter 32 via the noise suppression circuit 26, as illustrated in Figure 3.

35 Figure 9 is a schematic diagram illustrating the EEPROM 48 operating in conjunction with a thermocouple sensor 52. The EEPROM 48 operates in a similar

5 fashion as described in conjunction with Figure 7 and operates to enable calibration by clocking in the calibration coefficients from the processor 28. Subsequently the calibration coefficients data resident within the EEPROM 48 can be read-out to the memory 30 by the processor 28 for use in accurately calculating the temperature.

10 Although several embodiments of the invention have been disclosed for illustrative purposes, those skilled in the art will appreciate that various modifications, additions and substitutions are possible, without departing from the scope and spirit of the invention as defined in the accompanying claims.

5

## CLAIMS

1. A temperature sensing device (10), comprising:  
a sensor unit (14) including a sensor (16) operable to sense a temperature; and  
a memory (25) integral to the sensor unit (14), wherein the memory (25) contains  
nonlinear calibration data which characterize the sensor (16).
- 10 2. The temperature sensing device (10) of claim 1, wherein the nonlinear  
calibration data comprises historical data that reflects nonlinear behavior of a particular  
class of sensors.
3. The temperature sensing device (10) of claim 1, wherein the nonlinear  
calibration data comprises custom data which uniquely characterizes the sensor (16).
- 15 4. The temperature sensing device (10) of claim 1, wherein the nonlinear  
calibration data comprises a plurality of nonlinear calibration coefficients (42).
5. The temperature sensing device (10) of claim 1, further comprising a  
connector (20) for coupling a processor (28) to the sensor (16) and the memory (25),  
wherein the processor (28) is operable to access the nonlinear calibration data from the  
memory (25) and receive an electrical signal from the sensor (16) which is indicative of  
20 the temperature at the sensor (16), and to convert the electrical signal using the nonlinear  
calibration data into a temperature value which represents the temperature at the sensor  
(16).
6. The sensing device (10) of claim 5, further comprising a noise suppression  
25 circuit (26) coupled between the sensor (16) and the processor (28), wherein the noise  
suppression circuit (26) eliminates noise, thereby providing a filtered signal to the  
processor (28), and wherein the filtered signal is indicative of the temperature at the  
sensor (16).
7. The sensing device (10) of claim 5, further comprising an analog-to-digital  
30 converter (32) coupled between the sensor (16) and the processor (28), wherein the  
analog-to-digital converter (32) is operable to convert the electrical signal from the sensor  
(16) into a digital signal to be utilized by the processor (28).
8. The sensing device (10) of claim 5, further comprising a display (22)  
35 coupled to the processor (28) for displaying the temperature value which represents the  
temperature at the sensor (16).

- 5           9.     The sensing device (10) of claim 1, wherein the sensor (16) comprises a resistance temperature device (47).
10.    The sensing device (10) of claim 1, wherein the sensor (16) comprises a thermocouple device (52).
- 10          11.    The sensing device (10) of claim 1, wherein the memory (25) comprises an electrically erasable programmable read-only memory (48).
12.    A smart temperature sensor system (10), comprising:  
          a sensor (16) on a sensor unit (14), operable to sense a temperature;  
          a memory (25) on the sensor unit (14), wherein the memory (25) contains  
          nonlinear calibration data which characterizes the sensor (16); and  
15          a processor (28) remote from the sensor unit (14) in electrical communication with the sensor (16) and the memory (25), wherein the processor (28) receives the nonlinear calibration data from the memory (25) and an electrical signal from the sensor (16), and wherein the processor (28) utilizes the nonlinear calibration data to convert the electrical  
20          signal into a value that represents the temperature at the sensor (16).
13.    The smart temperature sensor system (10) of claim 12, wherein the nonlinear calibration data comprises historical data that reflects nonlinear behavior of a particular class of sensors.
14.    The smart temperature sensor system (10) of claim 12, wherein the  
25          nonlinear calibration data comprises custom data which uniquely characterizes the sensor (16).
15.    The smart temperature sensor system (10) of claim 12, wherein the nonlinear calibration data comprises a plurality of nonlinear calibration coefficients (42).
16.    The smart temperature sensor system (10) of claim 12, wherein the  
30          processor (28) communicates with the sensor (16) and the memory (25) through a wired connection (20).
17.    The smart temperature sensor system (10) of claim 12, wherein the processor (28) communicates with the sensor (16) and the memory (25) through an RF connection.
18.    The smart temperature sensor system (10) of claim 12, wherein the



5 processor (28) communicates with the sensor (16) and the memory (25) through an IR connection.

10 19. The smart temperature sensor system (10) of claim 12, further comprising a noise suppression circuit (26) coupled between the sensor (16) and the processor (28), wherein the noise suppression circuit (26) eliminates noise, thereby providing a filtered signal to the processor (28) which is indicative of the temperature at the sensor (16).

20 20. The smart thermal sensor system (10) of claim 12, further comprising an analog-to-digital converter (32) coupled between the sensor (16) and the processor (28), wherein the analog-to-digital converter (32) is operable to convert the electrical signal from the sensor (16) into a digital signal to be subsequently received by the processor (28).

15 21. The smart thermal sensing system (10) of claim 12, further comprising a display (22) coupled to the processor (28) for displaying a temperature value which represents the temperature at the sensor (16).

20 22. A method of calibrating a temperature sensor (16), comprising the steps of: measuring an output value of the temperature sensor (16) over a range of temperatures, thereby obtaining a plurality of paired data points (38,40); and utilizing the plurality of paired data points (38,40) in a mathematical curve fitting technique to obtain coefficients (42) to a polynomial that characterizes the performance of the sensor (16) over the temperature range.

25 23. The method of claim 22 further comprising the step of storing the coefficients (42) within a memory (25) associated with the sensor (16).

24. The method of claim 22, wherein the step of measuring the output value comprises measuring a voltage signal (40).

30 25. The method of claim 22, wherein the step of measuring the output value of the sensor (16) over a range of temperatures comprises:

measuring a voltage at a first known temperature in the temperature range;  
incrementing the temperature to a second known temperature in the temperature range;

measuring the voltage at the second known temperature; and

5 repeating the steps of incrementing the temperature and measuring the voltage at that temperature until the temperature range is traversed, thereby creating the plurality of paired data points (38,40).

26. The method of claim 22, wherein the step of measuring the output value comprises measuring a resistance.

10 27. The method of claim 22, wherein the step of utilizing the plurality of data points in a mathematical curve fitting technique comprises putting the data into a least squares fitting algorithm to calculate the polynomial coefficients (42).

15 28. The method of claim 27, wherein the polynomial is of a form  $T = C_0 + C_1 \cdot \text{EMF} + C_2 \cdot \text{EMF}^2 + C_3 \cdot \text{EMF}^3 + \dots + C_8 \cdot \text{EMF}^8$ , and wherein  $C_0, C_1, \dots, C_8$  are the coefficients.

29. The method of claim 27, further comprising the step of artificially weighing the least squares fitting algorithm so that the temperature at a voltage value of zero is zero degrees Celsius.

20 30. A method of making temperature measurements, comprising the steps of: sending at least one nonlinear calibration datum from a sensor (16) to a processor (28);

measuring a temperature with the sensor (16), wherein the sensor (16) converts the temperature to an electrical signal;

25 communicating the electrical signal from the sensor (16) to the processor (28); and converting the electrical signal into a temperature reading by utilizing the at least one nonlinear calibration datum in a conversion algorithm.

31. A method of providing custom calibration sensors (16) for measuring temperature, comprising the steps of:

30 measuring a voltage signal (40) of a thermal sensor (16) over a range of temperatures (38), thereby creating a plurality of paired data points (38,40);

calculating a plurality of custom nonlinear calibration coefficients (42) that are uniquely associated with the sensor (16) using the plurality of paired data points (38,40); and

35 storing the custom nonlinear calibration coefficients (42) in a memory (25) associated with the sensor (16).

- 5                   32.    A smart thermal sensing device (10), comprising:  
                  a sensor (16) on a sensor unit (14), wherein the sensor (16) is operable to sense a  
                  temperature; and  
                  a memory (25) on the sensor unit (14), wherein the memory (25) contains custom  
                  sensor data uniquely associated with the sensor (16), and wherein the custom sensor data  
10               comprises at least one of:  
                  one or more nonlinear calibration coefficients (42), a time constant,  
                  maintenance data, intended use environment data, regulatory data, or cold junction  
                  compensation coefficients.
-




FIGURE 1




FIGURE 2





FIGURE 3

2/4



279.4446	11.331	$C0 = 1.7005202 \times 10^{-6}$
279.4830	11.332	
258.8511	10.499	$C1 = 2.2218014 \times 10^{-1}$
258.8892	10.498	
233.8727	9.488	$C2 = -2.2030162 \times 10^0$
233.9105	9.487	
202.9652	8.485	$C3 = 4.4069171 \times 10^{-1}$
202.9948	8.486	
189.2702	7.701	$C4 = -3.6285769 \times 10^{-2}$
189.2702	7.701	
169.2302	6.902	$C5 = 1.0685829 \times 10^{-3}$
169.2202	6.909	
152.2747	6.231	$C6 = 0$
152.2773	6.232	
97.7441	4.005	$C7 = 0$
97.7596	4.005	
		$C8 = 0$

CALIBRATION  
TEMPERATURE  
(°C)

OUTPUT (mV)

COEFFICIENTS

FIGURES

3/4




FIGURE 6




FIGURE 7




FIGURE 8




FIGURE 9

# INTERNATIONAL SEARCH REPORT

International Application No  
PCT/US 97/17068

A. CLASSIFICATION OF SUBJECT MATTER  
IPC 6 G01K15/00

According to International Patent Classification (IPC) or to both national classification and IPC

## B. FIELDS SEARCHED

Minimum documentation searched (classification system followed by classification symbols)  
IPC 6 G01K G06F

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched

Electronic data base consulted during the international search (name of data base and, where practical, search terms used)

## C. DOCUMENTS CONSIDERED TO BE RELEVANT

Category	Citation of document with indication, where appropriate, of the relevant passages	Relevant to claim No
X	WO 94 12940 A (MCBEAN RONALD V) 9 June 1994  see page 7, line 19 - page 17, line 3; figures	1, 3, 5, 7, 8, 11, 12, 14, 16, 20-28, 30-32
A	US 5 361 218 A (TRIPP ROGER M ET AL) 1 November 1994 see the whole document	2, 4, 13, 15, 23

☐ Further documents are listed in the continuation of box C.

☒ Patent family members are listed in annex

### \* Special categories of cited documents:

- "A" document defining the general state of the art which is not considered to be of particular relevance
- "E" earlier document but published on or after the international filing date
- "L" document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)
- "O" document referring to an oral disclosure, use, exhibition or other means
- "P" document published prior to the international filing date but later than the priority date claimed

- "T" later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention
- "X" document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone
- "Y" document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art

"&" document member of the same patent family

Date of the actual completion of the international search

7 January 1998

Date of mailing of the international search report

20/01/1998

Name and mailing address of the ISA

European Patent Office, P.B. 5818 Patentlaan 2  
NL - 2280 HV Rijswijk  
Tel. (+31-70) 340-2040, Tx. 31 651 epo nl.  
Fax: (+31-70) 340-3016

Authorized officer

Ramboer, P



# INTERNATIONAL SEARCH REPORT

Information on patent family members

International Application No

PCT/US 97/17068

Patent document cited in search report	Publication date	Patent family members:	Publication date
WO 9412940 A	09-06-94	US 5347476 A	13-09-94
		AU 5676794 A	22-06-94
		EP 0671036 A	13-09-95
		JP 8503774 T	23-04-96
		US 5365462 A	15-11-94
		US 5375073 A	20-12-94
		US 5377128 A	27-12-94
US 5361218 A	01-11-94	NONE	

100

PCT

WORLD INTELLECTUAL PROPERTY ORGANIZATION  
International Bureau

## INTERNATIONAL APPLICATION PUBLISHED UNDER THE PATENT COOPERATION TREATY (PCT)

(51) International Patent Classification 6 :

G01K 15/00

A1

(11) International Publication Number:

WO 98/13677

(43) International Publication Date:

2 April 1998 (02.04.98)

(21) International Application Number: PCT/US97/17068

(22) International Filing Date: 24 September 1997 (24.09.97)

(30) Priority Data:  
08/718,921 25 September 1996 (25.09.96) US(71) Applicant: CLAUD S. GORDON COMPANY [US/US]; 5710  
Kenosha Street, Richmond, IL 60071 (US).(72) Inventor: SCHUH, William, C.; 218 Matthew Street, Delavan,  
WI 53115 (US).(74) Agent: ESCHWEILER, Thomas, G.; Renner, Otto, Boisselle  
& Sklar, P.L.L., 19th floor, 1621 Euclid Avenue, Cleveland,  
OH 44115 (US).(81) Designated States: AL, AM, AT, AU, AZ, BA, BB, BG, BR,  
BY, CA, CH, CN, CU, CZ, DE, DK, EE, ES, FI, GB, GE,  
GH, HU, IL, IS, JP, KE, KG, KP, KR, KZ, LC, LK, LR,  
LS, LT, LU, LV, MD, MG, MK, MN, MW, MX, NO, NZ,  
PL, PT, RO, RU, SD, SE, SG, SI, SK, SL, TJ, TM, TR,  
TT, UA, UG, UZ, VN, YU, ZW, ARIPO patent (GH, KE,  
LS, MW, SD, SZ, UG, ZW), Eurasian patent (AM, AZ, BY,  
KG, KZ, MD, RU, TJ, TM), European patent (AT, BE, CH,  
DE, DK, ES, FI, FR, GB, GR, IE, IT, LU, MC, NL, PT,  
SE), OAPI patent (BF, BJ, CF, CG, CI, CM, GA, GN, ML,  
MR, NE, SN, TD, TG).

Published


With international search report.

With amended claims.

Date of publication of the amended claims:

7 May 1998 (07.05.98)

(54) Title: SMART TEMPERATURE SENSING DEVICE



(57) Abstract

A smart temperature sensing device (10) includes a sensor (16) and a memory (25) on a sensor unit (14). The memory contains a plurality of custom nonlinear calibration coefficients which uniquely characterize the sensor (16). A temperature system includes the smart temperature sensing device (10) and a FSAU (12) having a processor (28) which downloads the calibration coefficients and utilizes them in converting electrical signals from the sensor (16) into temperature values that represent the temperature at the sensor (16). A method of calibrating a sensor (16) includes measuring an output signal of the sensor (16) over a temperature range, thereby obtaining a plurality of paired data points. The paired data points are used in a curve-fitting algorithm to obtain coefficients to a polynomial that characterizes the nonlinear temperature-voltage relationship of the sensor (16). The coefficients are stored within the memory (25) until downloaded by the processor (28) for use in signal conversion.

*FOR THE PURPOSES OF INFORMATION ONLY*

Codes used to identify States party to the PCT on the front pages of pamphlets publishing international applications under the PCT.

AL	Albania	ES	Spain	LS	Lesotho	SI	Slovenia
AM	Armenia	FI	Finland	LT	Lithuania	SK	Slovakia
AT	Austria	FR	France	LU	Luxembourg	SN	Senegal
AU	Australia	GA	Gabon	LV	Latvia	SZ	Swaziland
AZ	Azerbaijan	GB	United Kingdom	MC	Monaco	TD	Chad
BA	Bosnia and Herzegovina	GE	Georgia	MD	Republic of Moldova	TG	Togo
BB	Barbados	GH	Ghana	MG	Madagascar	TJ	Tajikistan
BE	Belgium	GN	Guinea	MK	The former Yugoslav Republic of Macedonia	TM	Turkmenistan
BF	Burkina Faso	GR	Greece	ML	Mali	TR	Turkey
BG	Bulgaria	HU	Hungary	MN	Mongolia	TT	Trinidad and Tobago
BJ	Benin	IE	Ireland	MR	Mauritania	UA	Ukraine
BR	Brazil	IL	Israel	MW	Malawi	UG	Uganda
BY	Belarus	IS	Iceland	MX	Mexico	US	United States of America
CA	Canada	IT	Italy	NE	Niger	UZ	Uzbekistan
CF	Central African Republic	JP	Japan	NL	Netherlands	VN	Viet Nam
CG	Congo	KE	Kenya	NO	Norway	YU	Yugoslavia
CH	Switzerland	KG	Kyrgyzstan	NZ	New Zealand	ZW	Zimbabwe
CI	Côte d'Ivoire	KP	Democratic People's Republic of Korea	PL	Poland		
CM	Cameroon	KR	Republic of Korea	PT	Portugal		
CN	China	KZ	Kazakhstan	RO	Romania		
CU	Cuba	LC	Saint Lucia	RU	Russian Federation		
CZ	Czech Republic	LI	Liechtenstein	SD	Sudan		
DE	Germany	LR	Liberia	SE	Sweden		
DK	Denmark			SG	Singapore		
EE	Estonia						

## AMENDED CLAIMS

[received by the International Bureau on 20 March 1998 (20.03.98);  
original claims 1 and 12 amended; remaining claims unchanged (5 pages)]

1. A temperature sensing device (10), comprising:  
a sensor unit (14) including a sensor (16) operable to sense a temperature; and  
a memory (25) integral to the sensor unit (14), wherein the memory (25) contains nonlinear calibration data which characterize the sensor (16) and wherein the nonlinear calibration data is independent of conversion circuitry for utilizing the nonlinear calibration data in generating an output indicative of the temperature.
2. The temperature sensing device (10) of claim 1, wherein the nonlinear calibration data comprises historical data that reflects nonlinear behavior of a particular class of sensors.
3. The temperature sensing device (10) of claim 1, wherein the nonlinear calibration data comprises custom data which uniquely characterizes the sensor (16).
4. The temperature sensing device (10) of claim 1, wherein the nonlinear calibration data comprises a plurality of nonlinear calibration coefficients (42).
5. The temperature sensing device (10) of claim 1, further comprising a connector (20) for coupling a processor (28) to the sensor (16) and the memory (25), wherein the processor (28) is operable to access the nonlinear calibration data from the memory (25) and receive an electrical signal from the sensor (16) which is indicative of the temperature at the sensor (16), and to convert the electrical signal using the nonlinear calibration data into a temperature value which represents the temperature at the sensor (16).
6. The sensing device (10) of claim 5, further comprising a noise suppression circuit (26) coupled between the sensor (16) and the processor (28), wherein the noise suppression circuit (26) eliminates noise, thereby providing a filtered signal to the processor (28), and wherein the filtered signal is indicative of the temperature at the sensor (16).
7. The sensing device (10) of claim 5, further comprising an analog-to-digital converter (32) coupled between the sensor (16) and the processor (28), wherein the analog-to-digital converter (32) is operable to convert the electrical signal from the sensor (16) into a digital signal to be utilized by the processor (28).

8. The sensing device (10) of claim 5, further comprising a display (22) coupled to the processor (28) for displaying the temperature value which represents the temperature at the sensor (16).
9. The sensing device (10) of claim 1, wherein the sensor (16) comprises a resistance temperature device (47).
10. The sensing device (10) of claim 1, wherein the sensor (16) comprises a thermocouple device (52).
11. The sensing device (10) of claim 1, wherein the memory (25) comprises an electrically erasable programmable read-only memory (48).
12. A smart temperature sensor system (10), comprising:
  - a sensor (16) on a sensor unit (14), operable to sense a temperature;
  - a memory (25) on the sensor unit (14), wherein the memory (25) contains nonlinear calibration data which characterizes the sensor (16) and wherein the nonlinear calibration data is independent of conversion circuitry for utilizing the nonlinear calibration data in generating an output indicative of the temperature; and
  - a processor (28) remote from the sensor unit (14) in electrical communication with the sensor (16) and the memory (25), wherein the processor (28) receives the nonlinear calibration data from the memory (25) and an electrical signal from the sensor (16), and wherein the processor (28) utilizes the nonlinear calibration data to convert the electrical signal into a value that represents the temperature at the sensor (16).
13. The smart temperature sensor system (10) of claim 12, wherein the nonlinear calibration data comprises historical data that reflects nonlinear behavior of a particular class of sensors.
14. The smart temperature sensor system (10) of claim 12, wherein the nonlinear calibration data comprises custom data which uniquely characterizes the sensor (16).
15. The smart temperature sensor system (10) of claim 12, wherein the nonlinear calibration data comprises a plurality of nonlinear calibration coefficients (42).
16. The smart temperature sensor system (10) of claim 12, wherein the processor (28) communicates with the sensor (16) and the memory (25) through a wired connection (20).

17. The smart temperature sensor system (10) of claim 12, wherein the processor (28) communicates with the sensor (16) and the memory (25) through an RF connection.
18. The smart temperature sensor system (10) of claim 12, wherein the processor (28) communicates with the sensor (16) and the memory (25) through an IR connection.
19. The smart temperature sensor system (10) of claim 12, further comprising a noise suppression circuit (26) coupled between the sensor (16) and the processor (28), wherein the noise suppression circuit (26) eliminates noise, thereby providing a filtered signal to the processor (28) which is indicative of the temperature at the sensor (16).
20. The smart thermal sensor system (10) of claim 12, further comprising an analog-to-digital converter (32) coupled between the sensor (16) and the processor (28), wherein the analog-to-digital converter (32) is operable to convert the electrical signal from the sensor (16) into a digital signal to be subsequently received by the processor (28).
21. The smart thermal sensing system (10) of claim 12, further comprising a display (22) coupled to the processor (28) for displaying a temperature value which represents the temperature at the sensor (16).
22. A method of calibrating a temperature sensor (16), comprising the steps of:  
measuring an output value of the temperature sensor (16) over a range of temperatures, thereby obtaining a plurality of paired data points (38,40); and  
utilizing the plurality of paired data points (38,40) in a mathematical curve fitting technique to obtain coefficients (42) to a polynomial that characterizes the performance of the sensor (16) over the temperature range.
23. The method of claim 22 further comprising the step of storing the coefficients (42) within a memory (25) associated with the sensor (16).
24. The method of claim 22, wherein the step of measuring the output value comprises measuring a voltage signal (40).
25. The method of claim 22, wherein the step of measuring the output value of the sensor (16) over a range of temperatures comprises:  
measuring a voltage at a first known temperature in the temperature range;

incrementing the temperature to a second known temperature in the temperature range;

measuring the voltage at the second known temperature; and

repeating the steps of incrementing the temperature and measuring the voltage at that temperature until the temperature range is traversed, thereby creating the plurality of paired data points (38,40).

26. The method of claim 22, wherein the step of measuring the output value comprises measuring a resistance.

27. The method of claim 22, wherein the step of utilizing the plurality of data points in a mathematical curve fitting technique comprises putting the data into a least squares fitting algorithm to calculate the polynomial coefficients (42).

28. The method of claim 27, wherein the polynomial is of a form  $T = C_0 + C_1 \cdot \text{EMF} + C_2 \cdot \text{EMF}^2 + C_3 \cdot \text{EMF}^3 + \dots + C_8 \cdot \text{EMF}^8$ , and wherein  $C_0, C_1, \dots, C_8$  are the coefficients.

29. The method of claim 27, further comprising the step of artificially weighing the least squares fitting algorithm so that the temperature at a voltage value of zero is zero degrees Celsius.

30. A method of making temperature measurements, comprising the steps of: sending at least one nonlinear calibration datum from a sensor (16) to a processor (28);

measuring a temperature with the sensor (16), wherein the sensor (16) converts the temperature to an electrical signal;

communicating the electrical signal from the sensor (16) to the processor (28); and

converting the electrical signal into a temperature reading by utilizing the at least one nonlinear calibration datum in a conversion algorithm.

31. A method of providing custom calibration sensors (16) for measuring temperature, comprising the steps of:

measuring a voltage signal (40) of a thermal sensor (16) over a range of temperatures (38), thereby creating a plurality of paired data points (38,40);



calculating a plurality of custom nonlinear calibration coefficients (42) that are uniquely associated with the sensor (16) using the plurality of paired data points (38,40); and

storing the custom nonlinear calibration coefficients (42) in a memory (25) associated with the sensor (16).

32. A smart thermal sensing device (10), comprising:

a sensor (16) on a sensor unit (14), wherein the sensor (16) is operable to sense a temperature; and

a memory (25) on the sensor unit (14), wherein the memory (25) contains custom sensor data uniquely associated with the sensor (16), and wherein the custom sensor data comprises at least one of:

one or more nonlinear calibration coefficients (42), a time constant, maintenance data, intended use environment data, regulatory data, or cold junction compensation coefficients.

**THIS PAGE BLANK (USPTO)**

**This Page is Inserted by IFW Indexing and Scanning  
Operations and is not part of the Official Record**

**BEST AVAILABLE IMAGES**

Defective images within this document are accurate representations of the original documents submitted by the applicant.

Defects in the images include but are not limited to the items checked:

- ☐ **BLACK BORDERS**
- ☐ **IMAGE CUT OFF AT TOP, BOTTOM OR SIDES**
- ☐ **FADED TEXT OR DRAWING**
- ☐ **BLURRED OR ILLEGIBLE TEXT OR DRAWING**
- ☐ **SKEWED/SLANTED IMAGES**
- ☐ **COLOR OR BLACK AND WHITE PHOTOGRAPHS**
- ☐ **GRAY SCALE DOCUMENTS**
- ☐ **LINES OR MARKS ON ORIGINAL DOCUMENT**
- ☐ **REFERENCE(S) OR EXHIBIT(S) SUBMITTED ARE POOR QUALITY**
- ☐ **OTHER:** \_\_\_\_\_

**IMAGES ARE BEST AVAILABLE COPY.**

**As rescanning these documents will not correct the image problems checked, please do not report these problems to the IFW Image Problem Mailbox.**

**THIS PAGE BLANK (USPTO)**